

High power short-time over current simulator

ICG 3000



- As per
- > GB/T17215.301
 - > GB/T17215.322
 - > ANCI C12 .02-2001

Description

ICG 3000 generates large power pulse over current for ammeter in the frequency range of 50Hz or 60Hz as per ANCI C12.02-2001.

- Features**
- > Protection for over voltage and over current
 - > LCD display, data acquisition of current and voltage
 - > Emergency stop button
 - > Built-in large power voltage change installation, controlled by CPU
 - > Large power IGBT semi-conductor switch, stable and safety
 - > As per GB/T17215.301, GB/T17215.322.

- Industries**
- > Communication
 - > Telecom
 - > Medical
 - > Broadcast
 - > Railway
 - > Technology
 - > Military
 - > Avionics
 - > New energy

Technical parameters	
Model	ICG 3000
Output voltage	0.01~3V
Output current	10~3000A
Output current resolution	0 ~ -10%
Output waveform	Sine wave
Output frequency	50Hz / 60Hz
Current injection time	1~9999ms or 0.1~500 cycle
Output impedance	0.001Ω
Output phase angle	0°
Test interval	3~9999s continuous adjustable
Number of test	1~9999
Test mode	Manual, automatic
Max. Power consumption	150~200KVA
Technical parameters	
Output current	10A 0 ~ -10%
	100A 0 ~ -10%
	1000A 0 ~ -10%
	2000A 0 ~ -10%
	30000A 0 ~ -10%
Output pulse width	1~9999ms

General data	
Power supply	AC220V ± 10%, 50/60Hz
Temperature	15~35℃
Humidity	25~75%
Air pressure	86kPa~106kPa
Dimension	1200*600*800 (22U)
Weight	280kg



CONNECT 3CTEST

SUZHOU3CTEST ELECTRONIC CO., LTD

Unit 2, Anda Industrial park, Jinshan Rd, SND, Suzhou, 215011, China
 Tel: +86-512-68413700/3800/3900
 Fax: +86-512-68079795
 Web: www.3ctest.cn
 Email: info@3ctest.cn

SHENZHEN OFFICE

Room 402, the 4th floor, Fuan Technology Building, No.13,
 Nanshan Technology Park, 518053, Shenzhen, China
 Tel: +86-755-86626625/ 86344313
 Fax: +86-755-26966255

HONGKONG OFFICE

One Commerce Center, 1201 Orange st, #600 Wilmington,
 New Castle, DE19899, USA
 Tel: +852-98289428
 Email: protech@protec-power.com Web: www.protec-power.com

Europe: AR Europe

Yvonne McGlinchey
 ymcglinchey@ARWorld.US
 +353 61 504300
 Address: First Floor Ashling Building, National Technology
 Park, Limerick, Ireland

BEIJING OFFICE

Room D206, D block, Keshi Building, No.28, Shangdixinxu
 Road, Haidian District, Beijing
 Tel: +86-10-82899948/ 82899984
 Fax: +86-10-82899943

CHENGDU OFFICE

Room 516, Unit 3, Ideal Centre, No.38 Tianyi Street, SND,
 6100085, Chengdu, China
 Tel: +86-28-85327800/85327600
 Fax: +86-28-85311400

TAIWAN OFFICE

6F-5, No.130, Ln.235, Baoqiao Rd,
 Xindian District, New Taipei City, 23145, Taiwan
 Tel: +886-2-89121185
 Email: rich.tec@msa.hinet.net